

## Bridge-W™ W500X Water Sensors Combo

### Bridge-W™ At-a-Glance

Bridge-W is a water detection system that includes five water detection sensors and a BridgeSecure Automated Alarm Central. The whole solution is wirelessly connected. BridgeSecure is a fully automated remote monitoring device that replaces a traditional remote monitoring service.

**Reduces losses & insurance premiums in:**

- Houses
- Condominiums
- Apartments

Bridge-W Water Sensors are designed to span large areas for maximized effectiveness. Alarms received from Bridge-W are automatically relayed by BridgeSecure like any other alarm. A list of 8 persons can be alerted by Voice, SMS and E-mail. Powerful and simple!

BridgeSecure configuration pages are accessible from a computer, tablet or cellphone. Type [bridgesecure/](http://bridgesecure/) in the address bar or use the device finder on our website at [bridgesecure.com/finder](http://bridgesecure.com/finder)

To allow automated voice calls, enter your VoIP account information or use an IP phone line.

Thanks to BridgeSecure self-checked firmware updates, you will always benefit from the latest features and improvements.

### 1 – Deploy the Bridge-W™ Water Sensors



### 2 – Pair with the BridgeSecure Alarm Central

To pair, just press the sensor's button. The sensor will send a unique serial N° that will appear on the configuration page. Select a zone name, and tap the Save button.

Sensors List (Group 00)

MY HOME SENSORS

✓ Help

Save Cancel

Sensor 001

DISHWASHER

Water leakage

AB:AB:CF

⌂

### 3 – Rest assured, leaks will be noticed!





**Contacts List**

Save Cancel

**Emergency Services Contact**

Contact Name

Phone Number  (Enter the emergency phone number for your area, usually 911)

If you use a VoIP phone service, make sure e911 Emergency Service is activated on your VoIP provider's account.

**Call Police Button**

Emergency > Contact 01 > Contact 02

**Medical Emergency Button**

Contact 01 > Emergency > Contact 02

**Fire Alarm**

Contact 01 > Emergency > Contact 02

(Choose call order for Medical and Fire alarms)

**Simple & Seamless**

Use the BridgeSecure configuration pages to enter who will be alerted by Voice, SMS and/or E-mail for each type of event. Optionally connect BridgeSecure to your home alarm system.

**Bridge-W Water Sensors Specifications**

Water alarm	Wireless + Audible
Low battery alert	Wireless + Audible
Loss of connection alert	24 hours
Range (open space)	Up to 150'
Sensor type	Industrial grade water sensing cable
No moisture retention	Yes
Total cable length / Sensor length	50" / 18"
Number of sensors and programmable zone names	Up to 32
Test button	Yes
Battery type	9V (6F22)
Battery life expectancy	5 Years

**In the box**

- 5 x W500X Bridge-W Water Sensors & Batteries
- B300X BridgeSecure Alarm Central
- Power adapter (micro USB plug)
- Blue network cable 6.5 feet

**Also includes (just in case)**

- Silver telephone cable 6.5 feet
- CA38A (RJ31X) telephone adapter
- Alarm panel telephone cable
- Quick start guide

Note: May be used with an IP phone Line or your VoIP account. Use your E-mail account for SMS and E-mail alerts.